

GOLF CART KEYLESS INSTRUCTION

Instruction



1. Power on by entering password

Touching numeric keyboard by 4 times, each touch as one single time with middle lights around the red circle twinkle and buzzing, the battery lights will be up one by one from left side to right side, after entering 4 numbers, touching the white button of red circle. If the password is correct, the lights around red circle will up and buzzing 2 seconds, power on; if the password was wrong, the lights around red circle twinkling, buzzing 2 seconds continuously till the lights down around red circle.



2. Setting to correct password

2 seconds to touch No.1 and No.4 at same time on keyboard, all lights up of keyless panel, buzzing 3 seconds and then the middle lights around red circle twinkling waiting for enter new password, re-touch a first new number with a buzzing and the left light up meanwhile the right 3 lights down of battery light. Touch a 2nd new number with a buzzing and the left 2 lights up meanwhile the right 2 lights down of battery lights, and so on, after entering 4 new numbers the battery lights are up and touch the white button of red circle with a buzzing. The password is correcting finished, all lights down, and exit setting.



3. Power off

In golf cart power on, touching the white button of red circle 3 seconds, buzzing 2 seconds, the lights down around red circle, then golf cart power off.



4. The initial password: 1234

INSTALLATION PROCEDURE

The Illustration



1



2



3



4



5



6

INSTALLATION PROCEDURE

Process



- 1 Unscrew and open the key ignition switch position shell cover right under the steering wheel.
- 2 Twist out the key switch,unplug the ignition wire.
- 3 Insert the keyless ignition switch into the key switch hole.
- 4 Connect the corresponding color ignition wires.
- 5 Close the shell cover.
- 6 Re-tighten the screws of the shell cover.





GOLF CART KEYLESS INSTRUCTION

- **Replace Your Key**
No more lost time or money replacing or searching for lost keys.
- **Pin Activated Ignition**
Restrict access to cart control with a secure programmable 4-digit user code.
- **Digital Battery Guide**
It uses cart power so there's no need to change batteries.
Monitor power levels with a light meter display guide.
- **Patented Technology**
Enjoy the keyless convenience of "one-button" cart activation
- **Power**
48 or 36V golf cart
Low power has 4 sections, the area 48V: 42-48V; 36V: 30V-36V



If there any issue with it, don't hesitate to contact us via Amazon message.
Your satisfaction is our greatest motivation!



**KEYLESS
IGNITION SWITCH**